


NOVACOR, INC.

OPTIMUM 386DXBB - 4A4B1

Processor	80386DX
Processor Speed	25/33/40MHz
Chip Set	OPTI
Max. Onboard DRAM	32MB
SRAM Cache	None
BIOS	MR
Dimensions	254mm x 218mm
I/O Options	None
NPU Options	3167



CONNECTIONS			
Purpose	Location	Purpose	Location
Turbo LED	CR1	Power LED & keylock	J19
External battery	J1	Turbo switch	JP3
Speaker	J18	Reset switch	SW1

Continued on next page . . .

NOVACOR, INC.
OPTIMUM 386DXBB - 4A4B1

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper	Position
í CMOS memory normal operation	JP1	pins 2 & 3 closed
CMOS memory clear	JP1	pins 1 & 2 closed
í Password select enabled	JP2	Closed
Password select disabled	JP2	Open

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
1MB	(4) 256K x 9	NONE
2MB	(4) 256K x 9	(4) 256K x 9
4MB	(4) 1M x 9	NONE
5MB	(4) 256K x 9	(4) 1M x 9
8MB	(4) 1M x 9	(4) 1M x 9
16MB	(4) 4M x 9	NONE
32MB	(4) 4M x 9	(4) 4M x 9