


OMNITEL, INC. 386 MODEL D

Processor 80386DX
Processor Speed 25/33MHz
Chip Set C & T
Max. Onboard DRAM 32MB
Cache None
BIOS Phoenix
Dimensions 355mm x 304mm
I/O Options None
NPU Options 80387/3167



CONNECTIONS			
Purpose	Location	Purpose	Location
Power LED & keylock	J16	Speaker	J19
Turbo LED	J17	External battery	J24
Reset switch	J18	Turbo switch	J30

Continued on next page . . .

OMNITEL, INC.

386 MODEL D

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper/Switch	Position
í BIOS type select 27512	J20	pins 2 & 3 closed
BIOS type select 27256	J20	pins 1 & 2 closed
í NPU type select 80387	J23	pins 1 & 2 closed
NPU type select 3167	J23	pins 2 & 3 closed
í POST enabled	J26	Closed
POST disabled	J26	Open
í Factory configured - do not alter	SW8/1	On
í Factory configured - do not alter	SW8/7	On
í Monitor type select monochrome	SW8/8	Off
Monitor type select color	SW8/8	On

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
1MB	(4) 256K x 9	NONE
2MB	(4) 256K x 9	(4) 256K x 9
4MB	(4) 1M x 9	NONE
8MB	(4) 1M x 9	(4) 1M x 9
16MB	(4) 4M x 9	NONE
32MB	(4) 4M x 9	(4) 4M x 9

DRAM SWITCH CONFIGURATION					
Size	SW8/2	SW8/3	SW8/4	SW8/5	SW8/6
1MB	Off	On	On	Off	Off
2MB	Off	On	On	Off	Off
4MB	Off	Off	On	Off	Off
8MB	Off	Off	On	Off	On
16MB	On	Off	Off	On	Off
32MB	On	Off	Off	On	Off