


# HEDAKA

## HED-986 (DIP VERSION)

<b>Processor</b>	80286
<b>Processor Speed</b>	12/16/20MHz
<b>Chip Set</b>	Hedaka
<b>Max. Onboard DRAM</b>	2MB
<b>Cache</b>	None
<b>BIOS</b>	AMI
<b>Dimensions</b>	330mm x 218mm
<b>I/O Options</b>	None
<b>NPU Options</b>	80287



CONNECTIONS			
Purpose	Location	Purpose	Location
Turbo LED	CN1	Auxiliary keyboard	CN7
Turbo switch	CN3	Power LED & keylock	CN9
Speaker	CN4	Speed display	CN12
Reset switch	CN5		

Continued on next page . . .

# HEDAKA

## HED-986 (DIP VERSION)

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper	Position
í Monitor type select color	JP8	pins 2 & 3 closed
Monitor type select monochrome	JP8	pins 1 & 2 closed
í NPU clock select internal oscillator	JP15	pins 2 & 3 closed
NPU clock select external oscillator	JP15	pins 1 & 2 closed
í NPU speed select OSC/1	JP14	pins 1 & 2 closed
NPU speed select OSC/3	JP14	pins 2 & 3 closed

DRAM CONFIGURATION				
Size	Bank 0	Bank 1	Bank 2	Bank 3
512KB	(4) 44256	NONE	NONE	NONE
1MB	(4) 44256	(4) 44256	NONE	NONE
1.5MB	(4) 44256	(4) 44256	(4) 44256	NONE
2MB	(4) 44256	(4) 44256	(4) 44256	(4) 44256

DRAM PARITY CONFIGURATION				
Size	P-0	P-1	P-2	P-3
512KB	(2) 41256	NONE	NONE	NONE
1MB	(2) 41256	(2) 41256	NONE	NONE
1.5MB	(2) 41256	(2) 41256	(2) 41256	NONE
2MB	(2) 41256	(2) 41256	(2) 41256	(2) 41256