


# XENER SUPER XT

<b>Processor</b>	8088
<b>Processor Speed</b>	10MHz
<b>Chip Set</b>	Unidentified
<b>Max. Onboard DRAM</b>	640KB
<b>Cache</b>	None
<b>BIOS</b>	Unidentified
<b>Dimensions</b>	220mm x 160mm
<b>I/O Options</b>	None
<b>NPU Options</b>	8087



CONNECTIONS			
Purpose	Location	Purpose	Location
Reset switch	JP2	Speaker	JP4

Continued on next page. . .

# XENER SUPER XT

... continued from previous page

DRAM CONFIGURATION				
Size	Bank 0	Bank 1	Bank 2	Bank 3
640KB	(2) 4164	(9) 41256	(9) 41256	(4) 4464

BIOS CONFIGURATION		
Size	JP1A	JP1B
2764/27128	Open	Open
27256	Closed	Open
27512	Closed	Closed

VIDEO CONFIGURATION		
Type	JP3A	JP3B
None	Closed	Closed
80 x 25 color	Open	Closed
40 x 25 color	Closed	Open
Monochrome/color	Open	Open