

# 6BX67

## Jumper Setting

Product name	Bus CLK	Multiplier	SW1 ( switch 1, 2, 3, 4 )	SW1 (Jumper 1, 2, 3, 4)
Pentium II-233	66	3.5X	1, 2	1, 2
Pentium II-266	66	4.0X	1, 3, 4	1, 3, 4
Pentium II-300	66	4.5X	1, 3	1, 3
Pentium II-333	66	5.0X	1, 4	1, 4
Pentium II-350	100	3.5X	1, 2	1, 2
Pentium II-400	100	4.0X	1, 3, 4	1, 3, 4
Pentium II-450	100	4.5X	1, 3	1, 3
Pentium II-500	100	5.0X	1, 4	1, 4
Pentium II-550	100	5.5X	1	1
Pentium II-600	100	6.0X	2, 3, 4	2, 3, 4

The M/B design Auto-Detect CPU Bus Clock 66 or 100 Mhz frequency NO jumper needed for setting