

Jumper settings for V4P895P3/SMT/V5.0 (4+2) Motherboard

Jumper	Cyrix 5x86/ DX4-100/120	AMD X5-133	AMD Enhanced CPU
JP3	1-2	1-2	1-2
JP4	OPEN	OPEN	OPEN
JP5	2-3	2-3	2-3
JP6	2-3	1-2	1-2
JP7	OPEN	1-2	1-2
JP8	1-2	1-2	1-2
JP9	1-2	2-3	2-3
JP12	OPEN	CLOSE	CLOSE
JP22	1-2	1-2	1-2
JP23	OPEN	CLOSE	CLOSE
JP24	OPEN	CLOSE	CLOSE
JP25	OPEN	CLOSE	CLOSE
JP27	OPEN	OPEN	OPEN
JP36	1-2	2-3	2-3
JP40	OPEN	OPEN	OPEN
JP43	OPEN	1-2	OPEN

--	--	--	--

Note:

1. The jumper setting should use together with BIOS v1.4 which is the same as the V4P895 (4x72) motherboard.
2. When use Cyrix 5x86-120, the sing on message will be Cx5x86 100M Hz, however, the performace will be at 120M Hz.
3. For 120M Hz CPU, the clock setting should be set to 40M Hz, for 100M Hz CPU and AMD X5-133 CPU, the clock should be set to 33M Hz.

Date: 31/1/96