


UNIDENTIFIED PVI-486AP4

Processor	80386SX
Processor Speed	25/33/40MHz
Chip Set	ALI
Max. Onboard DRAM	16MB
Cache	None
BIOS	AMI/Award
Dimensions	254mm x 218mm
I/O Options	None
NPU Options	80387SX



CONNECTIONS			
Purpose	Location	Purpose	Location
External battery	J4	Turbo switch & LED	J8
Reset switch	J6	Power LED & keylock	J9
Speaker	J7		

Continued on next page. . .

UNIDENTIFIED

PVI-486AP4

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper	Position
í NPU synchronous with CPU	JP2	pins 1 & 2 closed
NPU asynchronous with CPU	JP2	pins 2 & 3 closed
í CMOS memory normal operation	JP3	Open
CMOS memory clear	JP3	Closed
í Monitor type select color	JP4	pins 2 & 3 closed
Monitor type select monochrome	JP4	pins 1 & 2 closed
í Parity check enabled	JP6	Open
Parity check disabled	JP6	Closed
í TTL installed	JP7	Open
TTL not installed	JP7	Closed

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
512KB	(2) 256K x 9	NONE
1MB	(2) 256K x 9	(2) 256K x 9
2MB	(2) 1M x 9	NONE
4MB	(2) 1M x 9	(2) 1M x 9
8MB	(2) 4M x 9	NONE
16MB	(2) 4M x 9	(2) 4M x 9

CPU SPEED CONFIGURATION		
Speed	JP1	JP5
25MHz	pins 1 & 2 closed	pins 2 & 3 closed
33MHz	pins 2 & 3 closed	pins 2 & 3 closed
40MHz	pins 1 & 2 closed	pins 1 & 2 closed