


OLIVETTI M 1 9

| | |
|--------------------------|---|
| Processor | 8088 |
| Processor Speed | 4.77/8MHz |
| Chip Set | Unidentified |
| Max. Onboard DRAM | 640KB |
| Cache | None |
| BIOS | Unidentified |
| Dimensions | 330mm x 218mm |
| I/O Options | VGA port, IDE interface, Parallel port, Serial port |
| NPU Options | None |



| CONNECTIONS | | | |
|---------------|----------|-------------------------|----------|
| Purpose | Location | Purpose | Location |
| Speaker | CN1 | VGA port | CN4 |
| Parallel port | CN2 | IDE interface connector | CN5 |
| Serial port | CN3 | | |

Continued on next page. . .

**OLIVETTI
M 19**

... continued from previous page

| DRAM CONFIGURATION | | | | |
|--------------------|-----------|-----------|----------|----------|
| Size | Bank 0 | Bank 1 | Bank 2 | Bank 3 |
| 256KB | (9) 41256 | NONE | NONE | NONE |
| 640KB | (9) 41256 | (9) 41256 | (9) 4164 | (9) 4164 |

| DRAM JUMPER CONFIGURATION | | |
|---------------------------|--------|--------|
| Size | P2 | P3 |
| 256KB | Closed | Open |
| 640KB | Closed | Closed |

| CPU SPEED CONFIGURATION | | | | | | |
|-------------------------|--------|--------|--------|--------|--------|--------|
| Speed | SW1/1 | SW1/2 | SW1/3 | SW1/4 | SW1/5 | SW1/6 |
| 4.77Mhz | Closed | Closed | Closed | Closed | Open | Open |
| 8Mhz | Open | Open | Open | Open | Closed | Closed |

| CPU SPEED CONFIGURATION (CON'T) | | | | | | |
|---------------------------------|--------|--------|--------|--------|--------|--------|
| Speed | SW1/7 | SW1/8 | FSH1 | FSH2 | FSH3 | FSH4 |
| 4.77Mhz | Open | Open | Open | Closed | Open | Closed |
| 8Mhz | Closed | Closed | Closed | Open | Closed | Open |

| DISPLAY CONFIGURATION | | |
|-------------------------|--------|--------|
| Type | J1 | J2 |
| Monochrome | Closed | Open |
| Color | Open | Closed |
| External switch enabled | Open | Open |