

COMPAQ COMPUTER CORPORATION

PROLIANT 800

Processor	Pentium Pro
Processor Speed	180/200MHz
Chip Set	Unidentified
Video Chip Set	Unidentified
Maximum Onboard Memory	512MB (EDO supported)
Maximum Video Memory	2MB
Cache	256KB (located on Pentium Pro CPU)
BIOS	Unidentified
Dimensions	Unidentified
I/O Options	Unidentified
NPU Options	None

34368

CONNECTIONS

Note: The location and types of I/O options are unidentified.

USER CONFIGURABLE SETTINGS

Function	Label	Position
í Password normal operation	S1/1	Off
Password clear	S1/1	On
í Factory configured - do not alter	S1/3	On
í Factory configured - do not alter	S1/4	On
í Maintenance mode disabled	S1/7	Off
Maintenance mode enabled	S1/7	On
í Floppy drive boot disabled	S1/8	Off
Floppy drive boot enabled	S1/8	On

DIMM CONFIGURATION

Size	Bank 0	Bank 1	Bank 2	Bank 3
32MB	(1) 4M x 64	None	None	None
64MB	(1) 4M x 64	(1) 4M x 64	None	None
64MB	(1) 8M x 64	None	None	None
96MB	(1) 4M x 64	(1) 4M x 64	(1) 4M x 64	None
128MB	(1) 4M x 64	(1) 4M x 64	(1) 4M x 64	(1) 4M x 64
128MB	(1) 8M x 64	(1) 8M x 64	None	None
128MB	(1) 16M x 64	None	None	None
192MB	(1) 8M x 64	(1) 8M x 64	(1) 8M x 64	None
256MB	(1) 8M x 64	(1) 8M x 64	(1) 8M x 64	(1) 8M x 64
256MB	(1) 16M x 64	(1) 16M x 64	None	None
256MB	(1) 32M x 64	None	None	None
384MB	(1) 16M x 64	(1) 16M x 64	(1) 16M x 64	None
512MB	(1) 16M x 64	(1) 16M x 64	(1) 16M x 64	(1) 16M x 64

Note: Board accepts EDO memory.

CACHE CONFIGURATION

Note: 256KB/512KB cache is located on the Pentium Pro CPU.

Continued on next page . . .

COMPAQ COMPUTER CORPORATION
 PROLIANT 800

... continued from previous page

VIDEO MEMORY CONFIGURATION

Note: The location of the video memory is unidentified.

CPU SPEED SELECTION

CPU speed	Clock speed	Multiplier	S1/2	S1/5	S1/6
180MHz	60MHz	3x	Off	Off	On
200MHz	66MHz	3x	On	Off	On

NETWORK FREQUENCY SELECTION

Type	SW2
10Base T	All switches on
10Base 2	All switches on
100Base T	All switches off

SCSI ID SELECTION

SCSI ID	ID0	ID1	ID2
0	Off	Off	Off
1	On	Off	Off
2	Off	On	Off
3	On	On	Off
4	Off	Off	On
5	On	Off	On

TECHNICAL NOTE

Diagram not available.