

Jumper Setting Quick Reference

Main Memory Installation

SIMM A		SIMM B		RP SEL
SIMM 1 - SIMM 4	SIMM 5	SIMM 6		RP SEL
Installed	Not-Installed	Not-Installed		RP10
Not - Installed	S/S Used	S/S Used		RP8
Not - Installed	D/S Used	D/S Used		RP7
Installed	S/S Used	S/S Used		RP10
Installed	D/S Used	S/S Used		RP9

* S/S : Single Side 72-Pin SIMMs are all 1MB/4MB or 16MB Modules.
 * D/S : Double Side 72-Pin SIMMs are all 2MB/8MB or 32MB Modules.

RP15-RP19 : Cache Size Selection

Cache Memory Size	JP9	JP20	Tag RAM (U10)	Data RAM	RP SEL
64KB	1-2	1-2	8K*8 IPC	8K*8 8PCS (U11-U18)	RP15 short
128KB	2-3	1-2	8K*8 IPC	32K*8 4PCS (U11-U14)	RP16 short
256KB	2-3	1-2	32K*8 or 16K*8 IPC	32K*8 8PCS (U11-U18)	RP17 short
256KB	2-3	1-2	32K*8 or 16K*8 IPC	64K*8 4PCS (U11-U14)	RP18 short
512KB	2-3	2-3	32K*8 IPC	64K*8 8PCS (U11-U18)	RP19 short

